

## 25 Pair QWIK Cable™ Table for Toshiba CIX40

66 Block Pair	Color	Function	Connector	AMP Pin #	Mod Plug Pin #
1T	WH-BL	Station 1	AMP	26	
1R	BL-WH			1	
2T	WH-OR	Station 2	AMP	27	
2R	OR-WH			2	
3T	WH-GR	Station 3	AMP	28	
3R	GR-WH			3	
4T	WH-BR	Station 4	AMP	29	
4R	BR-WH			4	
5T	WH-SL	Station 5	AMP	30	
5R	SL-WH			5	
6T	RD-BL	Station 6	AMP	31	
6R	BL-RD			6	
7T	RD-OR	Station 7	AMP	32	
7R	OR-RD			7	
8T	RD-GR	Station 8	AMP	33	
8R	GR-RD			8	
9T	RD-BR	Station 9	AMP	34	
9R	BR-RD			9	
10T	RD-SL	Station 10	AMP	35	
10R	SL-RD			10	
11T	BK-BL	Station 11	AMP	36	
11R	BL-BK			11	
12T	BK-OR	Station 12	AMP	37	
12R	OR-BK			12	
13T	BK-GR	Station 13	AMP	38	
13R	GR-BK			13	
14T	BK-BR	Station 14	AMP	39	
14R	BR-BK			14	
15T	BK-SL	Station 15	AMP	40	
15R	SL-BK			15	
16T	YL-BL	Station 16	AMP	41	
16R	BL-YL			16	
17T	YL-OR	CO 1	RJ-14 2 Pair Plug		2
17R	OR-YL				3
18T	YL-GR	CO 2			4
18R	GR-YL				1
19T	YL-BR	CO 3	RJ-14 2 Pair Plug		2
19R	BR-YL				3
20T	YL-SL	CO 4			4
20R	SL-YL				1
21T	VI-BL	CO 5	RJ-11 1 Pair Plug		2
21R	BL-VI				3
22T	VI-OR	CO 6	RJ-11 1 Pair Plug		2
22R	OR-VI				3
23T	VI-GR	Analog Station #1	AMP	48	
23R	GR-VI			23	
24T	VI-BR	CO 7	RJ-11 1 Pair Plug		2
24R	BR-VI				3
25T	VI-SL	Analog Station #2	AMP	50	
25R	SL-VI			25	

Mike Sandman Enterprises, Inc. • Unique Telecom Products • 630-980-7710

[www.sandman.com](http://www.sandman.com)