

QWIK Cable™ - Mitel 3300 Cutdown

Connector Type	RJ-12 #	RJ-12 Pin	Mitel Circuit Type	Signal Type	Twenty five pair cable			RJ-21 male Amp con	66 Block
RJ-11	1	4	LSGS	LS 1 Tip	White/Blue	Tip 1	Pair 1	26	1
		3	LSGS	LS 1 Ring	Blue/White	Ring 1		1	2
RJ-11	2	4	LSGS	LS 2 Tip	White/Orange	Tip 2	Pair 2	27	3
		3	LSGS	LS 2 Ring	Orange/White	Ring 2		2	4
RJ-11	3	4	LSGS	LS 3 Tip	White/Green	Tip 3	Pair 3	28	5
		3	LSGS	LS 3 Ring	Green/White	Ring 3		3	6
RJ-11	4	4	LSGS	LS 4 Tip	White/Brown	Tip 4	Pair 4	29	7
		3	LSGS	LS 4 Ring	Brown/White	Ring 4		4	8
RJ-11	5	4	LSGS	LS 5 Tip	White/Slate	Tip 5	Pair 5	30	9
		3	LSGS	LS 5 Ring	Slate/White	Ring 5		5	10
RJ-11	6	4	LSGS	LS 6 Tip	Red/Blue	Tip 6	Pair 6	31	11
		3	LSGS	LS 6 Ring	Blue/Red	Ring 6		6	12
RJ-11	7	4	ONS	ONS 1 Tip	Red/Orange	Tip 7	Pair 7	32	13
		3	ONS	ONS 1 Ring	Orange/Red	Ring 7		7	14
RJ-11	8	4	ONS	ONS 2 Tip	Red/Green	Tip 8	Pair 8	33	15
		3	ONS	ONS 2 Ring	Green/Red	Ring 8		8	16
RJ-14	9	4	ONS	ONS 3 Tip	Red/Brown	Tip 9	Pair 9	34	17
		3	ONS	ONS 3 Ring	Brown/Red	Ring 9		9	18
		2	ONS	ONS 3 CS1	Red/Slate	Tip 10	Pair 10	35	19
		5	ONS	ONS 3 CS2	Slate/Red	Ring 10		10	20
RJ-14	10	4	ONS	ONS 4 Tip	Black/Blue	Tip 11	Pair 11	36	21
		3	ONS	ONS 4 Ring	Blue/Black	Ring 11		11	22
		2	ONS	ONS 4 CS1	Black/Orange	Tip 12	Pair 12	37	23
		5	ONS	ONS 4 CS2	Orange/Black	Ring 12		12	24
RJ-12	11	3	Relay 1/2	RLY1_Common	Black/Green	Tip 13	Pair 13	38	25
		4	Relay 1/2	RLY1_NO	Green/Black	Ring 13		13	26
		6	Relay 1/2	RLY1_NC	Black/Brown	Tip 14	Pair 14	39	27
		2	Relay 1/2	RLY2_Common	Brown/Black	Ring 14		14	28
		5	Relay 1/2	RLY2_NO	Black/Slate	Tip 15	Pair 15	40	29
RJ-12	12	3	Paging	Paging signal	Slate/Black	Ring 15		15	30
		4	Paging	Paging signal	Yellow/Blue	Tip 16	Pair 16	41	31
		2	Paging	Paging relay Com	Blue/Yellow	Ring 16		16	32
		5	Paging	NO pagong	Yellow/Orange	Tip 17	Pair 17	42	33
		1	Paging	NO paging	Orange/Yellow	Ring 17		17	34